

AUTOMATIC BATTERY CHARGER

Controlled by a microprocessor AUTO 110



20 Ah 110 Ah

Technical Data

- Input Voltage = 230 Volts Single Phase 50/60 Hz F
- Charging Voltage & Charging Current = 12 Volts 6 Amperes (EN 60335)
- Effective charging current (for information) = 9 Amperes
- For 12 Volts free electrolyte batteries or gel batteries
- All the free electrolyte batteries or gel batteries up to 110 Ah can be totally charged
- The charging of the battery is quite and totally controlled by the microprocessor, without disconnecting it
- Recommended by the battery manufacturers
- Copper coils
- Protected against short-circuit, polarity reversal and overload.
- There is a regulation with an automatic stop function after charging. The switched-on charger can remain indefinitely connected to the battery
- WU type charging curve
- Storage of cables on the back panel



Advantages

- Fully automatic battery charger
- The battery is perfectly charged without disconnecting it
- The electronics of your vehicle are protected
- No need to control the charging thanks to the microprocessor
- Time-saving
- There is no programming cancellation on the electronics.

Safety

- Charging in the reduced mode (with the green indicator light on). The ammeter allows viewing of the reduced mode
- Protection against polarity reversal (inversed clamps) : red indicator light on.
- Protection against short-circuit
- An indication of the presence of a network is shown by the green light flashing
- The ammeter indicating a current is displayed on the front
- The charging starts even if the battery is weak (2.5 Volts)
- Regulation of the outgoing current is at 13.8 Volts by reduction of the charging current.

Ref. 133 107

50/60 Hz V	V	110 W	20 Ah – 110 Ah	Charging	mm	kg
230	12	110 W	20 Ah – 110 Ah	6 A (EN 60335) 9 A effective	250 x 230 x 180	4



Z. I. du Robinson – 74150 VALLIÈRES / FRANCE
 Tel. 33 4 50 08 48 48 Fax 33 4 50 08 48 49
 www.ceval.fr



EN 60335-2-29